

POWERPRO



powerPRO Series Power Supplies

Instruction Manual

Catalogue Numbers

powerPRO300

powerPRO500

powerPRO3AMP

Record the following for your records:

Model _____

Catalogue No. _____

Date of Delivery _____

Warranty Period _____

Serial No. _____

Invoice No. _____

Purchase Order No. _____

Contents

| | |
|--|----|
| Instruction Manual | 1 |
| Catalogue Numbers | 1 |
| Contents | 2 |
| Safety Information | 3 |
| Precautions | 4 |
| Environmental Conditions | 4 |
| Avoiding Electrical Shock | 4 |
| Avoiding Damage to the Instrument | 4 |
| Equipment Operation | 5 |
| Symbols | 5 |
| Potential Risk and Preventive Measures | 6 |
| Risk assessment table | 6 |
| Preventative measures | 6 |
| Packing List | 7 |
| Specifications | 8 |
| Operating Instructions | 10 |
| Installation | 10 |
| Control Interface | 10 |
| Operation | 11 |
| Constant Mode | 11 |
| Program Mode | 13 |
| Typical Running Conditions | 14 |
| Troubleshooting | 16 |
| Care and Maintenance | 18 |
| Replacing the Fuses | 18 |
| Maintenance | 18 |
| Ordering information | 18 |
| Warranty | 19 |

Safety Information

Cleaver Scientific powerPRO Power Supply has been tested and found to comply with the limits for the CE regulation. Also, it is RoHS compliant to deliver confident product which meets the environmental directive. These limits are designed to provide reasonable protection against harmful interference when the instrument series is operated in a commercial environment. This instrument series used together with power supply unit generates, uses, and can radiate radio frequency energy, and if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this instrument series in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at their expense. Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. It is strongly recommended for the user to read the following points carefully before operating this equipment.

1. Read and follow the manual instructions carefully.
2. Do not alter the equipment. Failure to follow these directions could result in personal and/or laboratory hazards, as well as invalidate equipment warranty.
3. Use a properly grounded electrical outlet with correct voltage and current handling capacity.
4. Disconnect from power supply before maintenance and servicing. Refer servicing to qualified personnel.
5. Never use this instrument series without having the safety cover correctly in position.
6. Do not use the unit if there is any sign of damage to the external tank or cover. Replace damaged parts.
7. Do not use in the presence of flammable or combustible material; fire or explosion may result. This device contains components which may ignite such materials.
8. Refer maintenance and servicing to qualified personnel.
9. Ensure that the system is connected to electrical service according to local and national electrical codes. Failure to make a proper connection may create fire or shock hazard.
10. Use appropriate materials and operate correctly to avoid possible hazards of explosion, implosion or release of toxic or flammable gases arising from overheated materials.
11. The unit shall be operated only by qualified personnel.

Precautions

Use high level of precaution against any electrical device. Before connecting the electrical supply, check to see if the supply voltage is within the range stated at the rating label, and see to it that the device be seated firmly. Place the unit in a safe and dry location; it must NOT touch the surrounding. Follow the safety precautions for chemicals / dangerous materials. If needed, please contact qualified service representative or support@cleaverscientific.com

Environmental Conditions

Ensure the instrument is installed and operated strictly under the following conditions:

1. Indoor use only
2. $\leq 95\%$ RH
3. 75 kPa – 106 kPa
4. Altitude must not exceed 2000 meters
5. 4°C~ 40°C operating temperature
6. Pollution degree: 2
7. Mains supply voltage fluctuations up to $\pm 10\%$ of the normal voltage

Avoiding Electrical Shock

Follow the guidelines below to ensure safe operation of the unit.

The powerPRO Power Supply has been designed to utilize shielded wires thus minimizing any potential shock hazard to the user. Cleaver Scientific recommends against the use of unshielded wires.

To avoid electrical shock:

1. In the event of solution spilling on the instrument, it must be dried out for at least 2 hours and restored to NORMAL CONDITION before each operation.
2. Never connect or disconnect wires loading from the power jacks when the red indicator light of power switch is on.
3. WAIT at least 5 seconds after stopping a run before handling output leads or any connected apparatus.
4. ALWAYS make sure that your hands, work area, and instruments are **clean** and **dry** before making any connections or operating the power supply.
5. ONLY connect the power cord to a properly grounded AC outlet.

Avoiding Damage to the Instrument

1. Do not attempt to operate the device if damage is suspected.
2. Protect this unit from physical damage, corrosive agents and extreme temperatures (direct sunlight, etc.).
3. For proper ventilation and safety concerns, keep at least 10 cm of

space behind the instrument, and at least 5 cm of space on each side.

4. Use high level of precaution against the damages on the unit.
5. Do not operate the unit out of environmental conditions addressed above.
6. Do not operate the power supplies in high humidity environments (> 95%), or where condensation may occur.
7. To avoid condensation after operating the power supply in a cold room, wrap the unit in a plastic bag and allow at least 2 hours for the unit to equilibrate to room temperature before removing the bag and operating the unit.
8. Prior to applying any cleaning or decontamination methods other than manufacturer's recommendation, users should check with the manufacturer's instruction to see if the proposed method will damage the equipment.

Equipment Operation

Follow the guidelines below to ensure safe operation of the unit:

1. NEVER access dangerous chemicals or other materials to prevent possible hazard of explosion and damage.
2. Do not operate the unit without lids or covers to prevent possible hazards.
3. A temporary conductivity caused by condensation might occur even though this series is rated Pollution Degree 2 in accordance with IEC 664.

Symbols

Symbols used on the power supply are explained below.



Indicates an area where a potential shock hazard may exist.

Consult the manual to avoid possible personal injury or instrument damage.



Indicates disposal instruction.

DO NOT throw this unit into a municipal trash bin when this unit has reached the end of its lifetime. To ensure utmost protection of the global environment and minimize pollution, please recycle this unit.



Caution/ Warning: Indicates a hazardous situation which, if not avoided, could result in death or serious injury.

| | |
|---------------|--|
| powerPRO 300 | |
| | Max. voltage: 300 V Max. current: 700 mA Max. watt: 150 W |
| powerPRO 3AMP | |
| | Max. voltage: 300 V Max. current: 3000 mA Max. watt: 300 W |
| powerPRO 500 | |
| | Max. voltage: 500 V Max. current: 800mA Max. watt: 300W |

Potential Risk and Preventive Measures

Risk assessment table

| Frequency | Frequent | Likely | Possible | Rare | Unlikely |
|------------------------------|-----------------|---------------|-----------------|-------------|-----------------|
| Risk | | | | | |
| Bruise | | | √ | | |
| Slash | | | | | √ |
| Electrical shock | | | √ | | |
| Power cord plug wrong | | | | √ | |

Preventative measures

| Potential Risk | Preventive measures |
|------------------------------|---|
| Bruise | Do not put the machine near the table edge. |
| Slash | Prevent hard impact on the case. |
| Electrical Shock | Make sure that your hands, work area, and devices are clean and dry |
| Power cord plug wrong | Observe correct adapter plug. |

Packing List

powerPRO 300

- 1x powerPRO 300 Power Supply
- 1x Power Cord
- 1x Instruction Manual

powerPRO 3AMP

- 1x powerPRO 3AMP Power Supply
- 1x Power Cord
- 1x Instruction Manual

powerPRO 500

- 1x powerPRO 500 Power Supply
- 1x Power Cord
- 1x Instruction Manual

Packing List Checked by: _____

Date: _____

The packing lists should be referred to as soon as the units are received to ensure that all components have been included. The unit should be checked for damage when received.

Cleaver Scientific is liable for all missing or damaged parts / accessories within 7 days after customer received this instrument package. Please contact Cleaver Scientific immediately regarding this issue. If no response within such period from consignee party, that will be consignee party's whole responsibility.

Please contact your supplier if there are any problems or missing items.

Specifications

| | powerPRO 300 | powerPRO 3AMP | powerPRO 500 |
|---|---|--------------------------------------|--------------------------------------|
| Output Voltage / Inc | 5 - 300V / 1V | 5 – 300 / 1V | 5 – 500 / 1V |
| Output Current / Inc | 1 - 700mA / 1mA | 10 – 3,000mA / 10mA | 1 – 800mA / 10mA |
| Max. Watt | 150W | 300W | 300W |
| Rated Voltages | 100~ 240V; 47-60Hz, 200W: T2.5A/250V | 100-240V: 47- 60Hz,410W: T4A/250V | 100-240V: 47- 60Hz,400W: T4A/250V |
| Type of Output | 1. Voltage or Current with automatic crossover 2. When target constant mode is set, system automatically adjusts the two other parameter to maximum to allow constant run (later could be changed by user) | | |
| Program Storage | 30 programmed files | | |
| Program Multi-Step | Up to 6 steps | | |
| Editable Program Function | 1.Have typical running conditions program 2.Manual editable program | | |
| Display | 2.4" TFT | | |
| Control | Microprocessor controller | | |
| Safety Device | No Load detect | | |
| | Leakage detect | | |
| | Over temperature protection | | |
| | Over load detection | | |
| | Sudden load change detection (could be disabled by proper setting) | | |
| | Shrouded plugs and sockets | | |
| Timer | Constant: 1~999 mins with alarm, continuous Program: 1~999 mins with alarm, continuous | | |
| Crossover | Yes | | |
| Stackable | Yes | | |
| Automatic Recovery After Power Failure | Yes | | |
| IQ/OQ Protocols | Yes, optional | | |
| Regulatory | CE, ETL | CE | CE |
| Operating Temperature | 4°C~ 40°C | | |
| Construction Material | Flame retardant ABS faceplate | | |

| | |
|-----------------------|--------------------------------|
| Unit Dimension | 215 x 335 x 104 mm (W x L x H) |
| Weight | approx. 2.1 kg |

Cleaver Scientific powerPRO Series Power Supply are microprocessor controlled and designed to meet most electrophoresis needs. This manual describes the setup and operation of the powerPRO Series Power Supply including important information on safety and maintenance of the unit. The powerPRO Series Power Supply are capable of running horizontal & vertical electrophoresis, SDS-PAGE, native PAGE applications, two-dimensional electrophoresis, and electro-blotting. Furthermore, the powerful specifications plus five terminal pairs can be used for multi electrophoresis units simultaneously.

Cleaver Scientific powerPRO Series Power Supply provides Constant Voltage or Constant Current or Constant Power to instruments used in electrophoresis. 5 terminal pairs and the powerful specification equipped enable the maximum capability of powerPRO Series Power Supply compared to other existing similar product on the market.

Features of powerPRO Series Power Supply:


- Compact size
- Microprocessor controller
- Constant voltages, constant currents and constant power
- Five terminal outlets
- LCD display
- Timer with alarm function
- Advanced safety devices
- Stackability
- Wide applications for DNA, RNA and protein electrophoresis

Operating Instructions

Installation

powerPRO Series Power Supplies require no complex installation. As long as the unit is placed on a sturdy and level surface in a safe, dry place, and further connects with well-prepared electrophoresis systems, it is ready for operation.

Control Interface



| | | | |
|--|---|--|---|
| | Start Key: Press to activate or stop the unit | | Press to move cursor left between parameters |
| | Pause Key: Press to temporarily interrupt power to an operation in progress; resume power after pausing without resetting the timer | | Press to move cursor right between parameters |
| | Settings Key: Press to select either Constant/ Program Mode or Constant Voltage or Constant Current mode or Time | | Press to move cursor up between parameters and to increase numeric values |
| | Enter Key: Press to enter the numeric value set up | | Press to move cursor down between parameters and to decrease numeric values |

Operation


1. Place the unit on a sturdy and level surface in a safe, dry place, away from laboratory traffic.
2. Ensure that the AC power switch is OFF, and then plug the three-pronged power cord one end into a grounded three-prong AC outlet with appropriate voltage (100V to 240V as indicated on the rating sticker near the AC cord on the back of the unit) and plug the other end into the main power socket.
3. Connect the DC output jacks from the electrophoresis unit; insert the red lead (+) into the red output jack, and the black lead (-) into the black output jack.
4. Power on the unit by pressing the ON/OFF switch on the back.
5. The screen will show a loading screen for few seconds then enter to the mode-selecting page.

Constant Mode


Use the **Constant Voltage / Current / Power Operation** for applications that require only one specific voltage limit, current limit, and power limit continuously during the entire operation of electrophoresis.

Note: When target constant mode is set, system automatically adjusts the other two parameters to maximum to allow constant run. For example, if constant voltage is set, system will adjust current and power to the maximum value.

Users could later lower the other two values by themselves. System will hold the value either at target constant value or the one which has been reached first



1. Use the up and down arrow keys to select constant mode, then press the enter key to move to the next page.




2. Use the up and down arrows to select which parameter should be kept constant. Press the enter key to move to the next page.

| | |
|----|-----|
| V | 300 |
| mA | 700 |
| W | 150 |
| ⌚ | 0 |

3. Use the up and down arrows to navigate the parameters, press the enter key to start parameter adjustment.
4. Use the up and down arrows to adjust parameter values, then press the enter key to confirm.

Note: If the time value is set “0,” it indicates the power supplier will constantly operate until user manually stops it.



5. Press the start Key to begin electrophoresis. The LED next to the start key will light, indicating the power supply is active.

Parameter values can be viewed during the run.

| | |
|----|-----|
| V | 300 |
| mA | 700 |
| W | 150 |
| ⌚ | 0 |

6. Pressing the pause key will temporarily pause the run and will allow parameter values to be altered using the same method outlined above.


Pressing the start key will resume the run

COMPLETE


7. Upon completion of the run, an alarm will sound, and the screen will display “Complete”.
8. Press the start key to terminate the run and press the setting key to return to the settings screen.

Program Mode

The Program Mode allows you to vary levels in voltage (V), current (mA), and power (W) during specified time periods for up to 6 Steps, depending upon your electrophoresis needs. The powerPRO Series power supply is capable of having 30 different program files storages for user's convenience. After starting the operation, set the Program Mode as follow:



1. Use the up and down arrow keys to select program mode, then press the enter key to move to the next page.




2. Use the up and down arrows to select the desired program. Press the enter key to move to the next page.

| Program File: 30 | | | | | |
|------------------|-----|-----|-----|----|--|
| | V | mA | W | ⌚ | |
| 1 | 240 | 700 | 150 | 60 | |
| 2 | 170 | 700 | 150 | 60 | |
| 3 | 300 | 700 | 150 | 60 | |

3. Use the up, down left and right arrows to navigate the parameters, press the enter key to start parameter adjustment.
4. Use the up and down arrows to adjust parameter values, then press the enter key to confirm.

| Program File: 30 | | | | | |
|------------------|-----|-----|-----|----|--|
| | V | mA | W | ⌚ | |
| 4 | 300 | 700 | 150 | 50 | |
| 5 | 220 | 700 | 150 | 11 | |
| 6 | 130 | 700 | 150 | 34 | |

5. Navigate using the down arrow to set parameters for step 5 and 6.



- Press the start Key to begin electrophoresis. The LED next to the start key will light, indicating the power supply is active.

Parameter values can be viewed during the run.

| Program File: 30 | | | | |
|------------------|-----|-----|-----|----|
| | V | mA | W | ⌚ |
| 1 | 240 | 700 | 150 | 60 |
| 2 | 170 | 700 | 150 | 60 |
| 3 | 300 | 700 | 150 | 60 |

- Pressing the pause key will temporarily pause the run and will allow parameter values to be altered using the same method outlined above.


Pressing the start key will resume the run




- Upon completion of the run, an alarm will sound, and the screen will display "Complete".
- Press the start key to terminate the run and press the setting key to return to the settings screen.

Typical Running Conditions

Besides Constant Mode and Program Mode, powerPRO Power Supply provide a third option, **Typical Running Condition**. It is helpful for those users who are not familiar with the parameter settings and is convenience for a quick start.





- Use the up and down arrow keys to select typical running conditions mode, then press the enter key to move to the next page.





2. There are 4 categories that can be selected. Choose the model according to your experiment need.
3. After selecting model, the pre-set value will display. These values can be adjusted as described previously.
4. Press the start button to begin electrophoresis.

Troubleshooting

Many operating problems may be solved by carefully reading and following the instructions in this manual accordingly. Some suggestions for troubleshooting are given below. Should these suggestions not resolve the problem, contact our service department or a distributor in your region for assistance. If troubleshooting service is required, please include a full description of the problem.

| Problem | Possible Causes | Solution |
|--|---|--|
| No Display / lights | No AC power | Check if powerPRO power supply is plugged, or AC power source has problem. |
| | AC power cord is not connected | Check AC power cord connections at both ends. Use the correct cords. |
| | The fuse has blown | Replace the fuse. |
| Repeated fuse broken | Hardware failure | Contact Cleaver Scientific service department |
| Operation stops and the screen displays  | Communication wires on circuit board have loosen or broken. | It is recommended to send the machine back to local distributor or our Service Department for maintenance. |
| Operation stops with alarm: The screen displays  | Electrophoresis leads are not connected to the power supply or to the electrophoresis unit(s), or there is a broken circuit in the electrophoresis cell | Check the connections to the power supply and on your electrophoresis cell to make sure the connection is intact; check condition of wires in electrophoresis unit. Close the circuit by reconnecting the cables. Press START/STOP to restart the run. |
| | High resistance due to tape left on a pre-cast gel, incorrect buffer concentration, or incorrect buffer volumes in the electrophoresis cell | Make sure the tape is removed from the pre-cast gel, buffers are prepared correctly, and the recommended volume of buffer is added to the electrophoresis unit. |
| | High voltage application is set to run on a very low current | DISABLE No Load alarm on the Display Screen |
| Operation stops with alarm. Display shows | Bad connections for terminal connectors or damaged wires or damaged platinum wires | Check all the connections to terminators, cables, wires, and gel tanks |

| | | |
|---|--|---|
| <p>LOAD CHANGED</p> | | |
| <p>Operation stops with alarm: Display shows</p> <p>OVER VOLTAGE</p> | <p>Circuit is interrupted</p> | <p>Verify that the running buffer is correct. Verify the all cables are attached correctly Turn the Power switch off and on again; restart application. If you cannot restart the instrument, turn off the power, disconnect the power cord from the outlet, and contact Technical Service.</p> |
| <p>Operation stops with alarm: Display shows</p> <p>OVER CURRENT</p> | <p>Circuit is interrupted</p> | <p>Verify that the running buffer is correct. Verify the all cables are attached correctly Turn the Power switch off and on again; restart application. If you cannot restart the instrument, turn off the power, disconnect the power cord from the outlet, and contact Technical Service.</p> |
| <p>Operation stops with alarm: Display shows</p> <p>LEAKAGE</p> | <p>Ground leak detected during run</p> | <p>Check the electrophoresis system for improper grounding. Restart the power supply by turning the Power switch off and on.</p> |
| <p>Operation stops with alarm: Display shows</p> <p>OVER TEMPERATURE</p> | <p>Power supply is overheating</p> | <p>Turn off power supply. Check for sufficient airflow around the power supply fan. After cooling down, restart the power supply by turning the Power switch to the on position. If you cannot restart the instrument, turn off the power, disconnect the power cord from the outlet, and contact Technical Service.</p> |
| <p>Warning message displays with 5-second beep sound. The screen shows</p> <p>Power Recovery</p> | <p>The power once been cut and now recover</p> | <p>User does not need to take extra action. The warning sign and beep sound would only last for 5 second; after that, the machine will continue running the unfinished project.  The  sign indicates the machine has been interrupted by sudden power off. Press Enter Key  to clear the sign.</p> |

Care and Maintenance

Replacing the Fuses

1. Turn off the main power switch at the rear of Power Supply and detach the power cord.
2. Open the fuses compartment located inside the Power Entry Module by inserting a small flat blade screwdriver into the slot above the ON/OFF switch. Turn the screwdriver to gently pry open the fuses compartment.

Note: The fuses compartment will not open with the power cord in place.

1. Pull the fuses holder out of the compartment and inspect the fuses. If the fuses are burned or there is a break in the fuses element, replace the fuses with identical type of fuses.
2. Place the fuses holder back into the compartment.
3. Snap the cover closed.

For additional fuses, contact Cleaver Scientific

Maintenance

powerPRO Series Power Supply uses all solid-state components and should require no maintenance or recalibration under normal use. If the unit must be returned for repair, contact our service department or your local distributor for shipping instruction.

Ordering information

| Cat. No. | Description |
|---------------------|---------------------------------|
| PowerPro300 | 300V, 700mA, 150W Power Supply |
| PowerPro3AMP | 300V, 3000mA, 300W Power Supply |
| PowerPro500 | 500V, 800mA, 300W Power Supply |

Warranty

The Cleaver Scientific Ltd. (CSL) powerPRO units have a warranty against manufacturing and material faults of twelve months from date of customer receipt.

If any defects occur during this warranty period, CSL will repair or replace the defective parts free of charge.

This warranty does not cover defects occurring by accident or misuse or defects caused by improper operation.

Units where repair or modification has been performed by anyone other than CSL or an appointed distributor or representative are no longer under warranty from the time the unit was modified.

Units which have accessories or repaired parts not supplied by CSL or its associated distributors have invalidated warranty.

CSL cannot repair or replace free of charge units where improper solutions or chemicals have been used. For a list of these please see the Care and Maintenance subsection.

If a problem does occur, then please contact your supplier or Cleaver Scientific Ltd:

Cleaver Scientific Ltd.

Unit 41, Somers Road Industrial Estate

Rugby, Warwickshire, CV22 7DH

Tel: +44 (0)1788 565300

Email: info@cleaverscientific.com